First National Bank of Baird
P.O. Box 968
Baird, TX 79504

Sharp BancSystems

Booting and Taking Down the Computer

NOTICE

This material is the exclusive confidential property of Sharp BancSystems. All rights are reserved by Sharp BancSystems.

Reproduction of this documentation is strictly prohibited

1. Locate the power on switch and turn the computer on. After a moment, see displayed on the console CRT:

   ```
   Boot
   :
   ```

2. Make sure your caps-lock key if off so that everything you may type in is in lower case letters. Also make sure your num-lock is on so that the numeric keypad will be entering numbers.

3. Press the ENTER key. If the computer was shut down properly the last time, the following message will not appear; proceed to step 5. If not (such as a power outage) the following will appear on the console CRT:

   ```
   The system was not shut down properly, and the root file system needs cleaning.
   Proceed with cleaning (y/n)?
   ```

4. Always answer this question y and press ENTER. On certain instances when the computer cleans the file systems, it will return to step 2 instead of going on to step 5. Also when the computer cleans the file systems, you may also see this message elsewhere in the boot procedure:

   ```
   NEED SCRATCH FILE (XX BLKS)  ENTER FILENAME:
   ```

   If you see this message, type in scratch and press the ENTER key.

   Certain other questions about "repairing a file" or "clearing a file", etc., might appear. Always answer these questions with Y.

5. See displayed on the console CRT:

   ```
   Type CONTROL-d to continue with normal startup,
   (or give the root password for system maintenance):
   ```

6. Hold down the Ctrl key and press d. This will not echo anything on the console CRT. If by mistake you enter the login id 'root' password you will get a # prompt; just type Ctrl-d to proceed normally. See the following displayed on the console CRT:

   ```
   Current system time is Wed Nov 3 14:36:23 PST 1985
   Enter time ([yymmdd]hhmm):
   ```

7. Always press ENTER to take the data and time that is displayed. If the date or time needs changing, you must change it in the computer's BIOS setup.

8. When the following is displayed on your console CRT, the computer is up and you will be able to log in on any and all CRT's.

   ```
   login:
   ```

1. Log out of your current account and log into root login id (see separate instructions, Logging On the Computer and Logging Off the Computer). Notice your prompt will be #.

2. Make sure that no one is running a program at any other terminal. They should be logged off the computer or at least back to the main menu program or the Sharp Bank Accounting System Main Menu. Type in the following:

   shutdown -g0 (numeric 0, then press ENTER (for UNIX systems)

3. When the following is displayed on the console CRT, it is safe to power off the computer:

   ** Normal System Shutdown **
   ** Safe to Power Off **
   -or-
   ** Press Any Key to Reboot **